

## Time Redirect Override

The **Night** feature has three states – normal, temporary or permanent, which are changed when the Night button is pressed. The states are shown as follows:

- Normal = no stars (this means the display is blank in Day mode and shows Night in Night mode)
- Temporary = one star in front of word Night (this applies whether the mode was changed from Day to Night or Night to Day)
- Permanent = two stars in front of word Night (this applies whether the mode was changed from Day to Night or Night to Day)

These modes are defined by the service provider and can be configured for different time periods.

The following table shows how to activate the various states of Night mode.

<b>State</b>	<b>Activation</b>	<b>Definition</b>	<b>Example</b>
Normal	Default state, no activation required	Routes calls appropriately based on the time-of-day and day-of-week.	Monday-Friday 8-5, calls go to attendant's phone. All other times, calls are answered by auto-attendant.
Temporary (*Night)	Press the <b>Night</b> soft key once.	Changes the mode, but will automatically revert back to the Normal state at the next change in the time-of-day/day-of-week schedule.	Attendant leaves early Monday and activates Night mode. The system automatically returns to normal at 8 a.m. Tuesday morning.
Permanent (**Night)	Press the <b>Night</b> soft key twice	Changes the mode, but requires manual intervention to return to the Normal state.	Attendant will be out for several days and no one will answer the main number. Attendant uses Permanent Night mode, which remains in effect until the Night soft key is pressed again.
Return to Normal	Press the <b>Night</b> soft key twice.	Night mode is disabled, whether it is Temporary or Permanent.	